

# NIR RETRO-REFLECTIVE PHOTOEYE

## NIR RETRO-REFLECTIVE PHOTOEYE

- Flexible voltage 12 Volt AC/DC to 240 Volt AC 40mA current draw.
- Watertight package.
- Detection range up to 30 feet.
- 6 feet of lead wire.
- Bracket and mounting hardware included.
- Two LED indicators
- Sensitivity adjustment
- Compact package. Size: 2.5" High, 1.5" Deep, 0.75" Wide



## APPLICATIONS

The NIR Retro-Reflective Photoeye may be used as a reversing sensor for:

- Commercial overhead doors
- Gates
- Parking Barriers

## TECHNICAL SPECIFICATIONS

**Operating Temperature:** -20° C to +55°C (-4°F to +131°F)

**Operating Voltage:** 12 – 240 Volts DC, 24 – 240 Volts AC

**Dimensions:** H = 2.5", D = 1.5", W = 0.75"

**Lead Wire:** 6 feet

**Response Time:** 10 ms maximum

**Fail Safe Relay Output:** 125V AC 0.6A, 110V DC 0.6A, 30V DC 2A.

**Environmental Protection:** IP66 (IEC)

**Certifications:** CE

WE ACCEPT MASTERCARD, VISA AND AMERICAN EXPRESS CREDIT CARD ORDERS.

\* NOT FOR USE IN APPLICATIONS REQUIRING UL325 APPROVAL.

**EMX INDUSTRIES, INC.**  
4564 Johnston Parkway  
Cleveland, Ohio 44128

Telephone:  
1-800-426-9912  
216-518-9888

Fax: 216-518-9884

Email: [salesupport@emxinc.com](mailto:salesupport@emxinc.com)

WEB: <http://www.emxinc.com>

Technical Support:  
[technical@emxinc.com](mailto:technical@emxinc.com)

**EMX**  
INDUSTRIES, INC.

# NIR RETRO-REFLECTIVE PHOTOEYE

## ACCESSORIES



**Reflector O-HD**  
(Hood shown with Reflector-O installed)



**NIR-HD**



**Reflector-O**



**NIR-BR**

## WARRANTY

EMX INC. the product described herein for a period of 2 years under normal use and service from the date of sale to our customer. The product will be free from defects in material and workmanship. This warranty does not cover ordinary wear and tear, abuse, misuse, overloading, altered products, or damage caused by the purchaser from incorrect connections, or lightning damage.

There is no warranty of merchantability. There are no warranties expressed, implied or any affirmation of fact or representation which extend beyond the description set forth herein.

EMX Inc. sole responsibility and liability, and purchaser's exclusive remedy shall be limited to the repair or replacement at EMX's option of a part or parts not so conforming to the warranty. In no event shall EMX Inc. be liable for damages of any nature, including incidental or consequential damages, including but, not limited to any damages resulting from non-conformity defect in material or workmanship.